information reference signal resource by the first transmission point, wherein the user device measures and returns the first precoding matrix indicator along with a first channel quality indicator and first reference index; and

the second precoding matrix indicator is computed by the user device based on a transmission of the second channel state information reference signal resource by the second transmission point, wherein the user device measures and returns the first precoding matrix indicator along with a first channel quality indicator and first reference index.

3. The apparatus of claim **2**, wherein:

the third precoding matrix indicator is computed based on substantially simultaneous respective transmissions by the first and second transmission points over one port of a third channel state information reference signal resource.

4. The apparatus of claim **3**, wherein the third channel state information reference signal resource comprises a two-port reference signal with one port from the first transmission point and one port from the second transmission point.

5. The apparatus of claim **1**, wherein the third precoding matrix indicator is based on simultaneous transmission of a rotation precoding vector by the first and second transmission points.

6. The apparatus of claim **5**, wherein the rotation precoding vector is:

$$R_1 = R_2^H = \begin{bmatrix} 1.0000 & 0.3334 - 0.4714i \\ 0.3334 - 0.4714i & 0.3332 + 0.9429i \end{bmatrix}.$$

7. A method comprising:

computing a co-phasing coefficient value for maximizing signal to noise ratio of a composite channel for transmission to a user device, the composite channel comprising first and second transmission points, wherein computing the co-phasing value comprises:

receiving first, second, and third precoding matrix indicators, wherein the third precoding matrix indicator is computed based on transmission of the first and second precoding matrix indicators over a joint channel state information reference signal resource from first and second transmission points; and

calculating the co-phasing coefficient value based on the first, second, and third precoding matrix indicators;

wherein the first and second precoding matrix indicators are computed based on feedback by a user device based, respectively, on transmissions of first and second channel state information reference resources from first and second transmission points, respectively.

8. The method of claim **7**, wherein:

the first precoding matrix indicator is computed by the user device based on a transmission of the first channel state information reference signal resource by the first transmission point, wherein the user device measures and returns the first precoding matrix indicator along with a first channel quality indicator and first reference index; and

the second precoding matrix indicator is computed by the user device based on a transmission of the second channel state information reference signal resource by the second transmission point, wherein the user device measures and returns the first precoding matrix indicator along with a first channel quality indicator and first reference index.

9. The method of claim **8**, wherein:

the third precoding matrix indicator is computed based on substantially simultaneous respective transmissions by the first and second transmission points over one port of a third channel state information reference signal resource.

10. The method of claim **9**, wherein the third channel state information reference signal resource comprises a two-port reference signal with one port from the first transmission point and one port from the second transmission point.

11. The method of claim **1**, wherein the third precoding matrix indicator is based on simultaneous transmission of a rotation precoding vector by the first and second transmission points.

12. The method of claim **11**, wherein the rotation precoding vector is:

$$R_1 = R_2^H = \begin{bmatrix} 1.0000 & 0.3334 - 0.4714i \\ 0.3334 - 0.4714i & 0.3332 + 0.9429i \end{bmatrix}.$$

13. A computer readable medium storing a program of instructions, execution of which by a processor configures an apparatus to at least:

compute a co-phasing coefficient value for maximizing signal to noise ratio of a composite channel for transmission for transmission to a user device, the composite channel comprising first and second transmission points, wherein computing the cophasing value comprises:

receiving first, second, and third precoding matrix indicators, wherein the third precoding matrix indicator is computed based on transmission of the first and second precoding matrix indicators over a joint channel state information reference signal resource from first and second transmission points; and

calculating the co-phasing coefficient value based on the first, second, and third precoding matrix indicators;

wherein the first and second precoding matrix indicators are computed based on feedback by a user device based, respectively, on transmissions of first and second channel state information reference resources from first and second transmission points, respectively.

14. The computer readable medium of claim **13**, wherein:

the first precoding matrix indicator is computed by the user device based on a transmission of the first channel state information reference signal resource by the first transmission point, wherein the user device measures and returns the first precoding matrix indicator along with a first channel quality indicator and first reference index; and